

## CANTO PLUS ESPRESSO

<b>Version</b>	<b>Espresso</b>
Cups Capacity	650 / 750 - 8 OZ or 450 - 12 OZ
<b>Stirrer capacity</b>	<b>Up to 1,100</b> <b>(2 columns with 550 each)</b>
No. of canisters	8 basically but up to 10
<b>User interface</b>	<b>Direct selections</b>
Pushbuttons	Up to 22
<b>Coffee unit</b>	<b>New Z4000:</b> <b>Small chamber (6-9 grams)</b> <b>Big chamber (7-15 grams)</b>
Pressure boiler:	200 cc / 600 cc
<b>Cooling Unit</b>	<b>As optional</b>
Communication Protocol	Executive - BDV - MDB
<b>New Aesthetics</b>	<b>Collage or Dolce Vita</b> <b>(Gold as optional)</b>
2 LED backlit panels	.
<b>New guided LED interface</b>	.
New graphic display with 10 lines and 20 characters (small images or icons can be displayed)	320 x 240 pixels
<b>Colour screen available as optional</b>	<b>it can be integrated in the user's interface and can play advertising videos or images</b>
New N&W electronic platform with advanced 16 bit technology	.
<b>Delivery Area</b>	<b>Vend door - Cup sensor - Light - Jug Facility - Free Vend available for some countries</b>
Height	1830 mm
<b>Width</b>	<b>650 mm</b>
Depth	760 mm
<b>Depth with door open</b>	<b>1320 mm</b>
Weight	170 kg
<b>Optional Accessories</b>	<b>Infrared kit for cup detection</b> <b>Lid and lock for coin box kit</b> <b>Video kit for user interface area</b> <b>Delivery area lighting kit</b> <b>Water tank kit</b> <b>Cooling unit (Still or Carbonated)</b> <b>Kit IRDA Kit jack (RS232-jack)</b> <b>Automatic slider</b> <b>Bank kit (to provide a mechanical link with a Samba)</b> <b>Hot water kit</b> <b>Internal lamp</b> <b>Switch to store door openings' time in the statistics</b> <b>Heating element for soluble powders</b> <b>(to allow the machine to work with 35° C T and 85% R.U.)</b> <b>Self adjusting coarseness kit</b>

